

The 4/2 to Contact ID (CID) conversion template maps 4/2 pulse event codes to their corresponding Contact ID event codes, enabling consistent translation of security events. Technicians **MUST** download and apply the updated template to all associated StarLink radio communicators to ensure accurate event reporting to the central station. **Events will NOT be reported if the modified template is not applied!**

See the **SLE Series Radio Reporting & PCD-Windows Quick-loader Setup and Configuration Instructions (WI2140)** for more information about how the NAPCO NOC (www.NapcoNoc.com) forwards alarm signals to the central station via Contact ID and 4/2.

Before powering the StarLink communicator, you must first be an active NAPCO StarLink dealer and have a StarLink account registered at www.NapcoComNet.com. In addition, the StarLink communicator radio ID# must be registered in your account.

First, log in to the NAPCO NOC website (www.NapcoNoc.com).

1. In the **Advanced** tab, scroll down and add a check to the **Convert Pulse to CID** checkbox.

Handshake Configuration

Handshake Kissoff: HS2 CID, 2300, 1400 (132)

Convert Pulse to CID:

Miscellaneous Code: 790 890 Y

Pulse Conversion Settings

2. Select the **Pulse Conversion Settings** button (shown above) to manage the conversion of 4/2 to CID codes.

STARLINK RADIO MANAGEMENT CENTER [SQA 25.11] Welcome DBLOCK12 | [Logout]

Home Radio Programming Radio Pulse Code

RADIO INFORMATION

Radio Serial# 15539946
 ICCID# 0000080809062181238
 Dealer ID: 8006459443
 Status: Active
 IP Address: 10.72.173.69

Template: Dave **Manage Template** Upload from Radio Download To Radio

Code Types: ALL
 Pulse Code: Search

All Assigned Not Assigned

Notes:
 The Pulse-to-Contact ID conversion template maps Pulse event codes to Contact ID codes for accurate event reporting. Technicians must download and apply the updated template to all associated radio modules; otherwise, default or previously configured codes will be used. Dealers are responsible for testing all event codes — NAPCO is not liable for incorrect or missing entries.

| Pulse Code | Code Type | Code Name | Default Code | Template Code | Radio Stored Code |
|------------|-----------|---------------|--------------|---------------|-------------------|
| 11 | Alarm | Keypad Fire | 179AA981 | 113AA1AA | 113AA1AA |
| 12 | Alarm | Not Define 12 | 179AA981 | 179AA981 | 113AA981 |
| 13 | Alarm | Not Define 13 | 179AA981 | 179AA981 | 179AA981 |

3. To download and view the Pulse 4/2 and CID code conversions stored in the communicator, select a template from the **Template** dropdown and select **Manage Template** (circled above) and the screen shown below opens. In the **Template** dropdown shown below, select a template (changes to the Default Template are not permitted).

STARLINK RADIO MANAGEMENT CENTER [SQA 25.11] Welcome DBLOCK12 | [Logout]

Pulse to CID Conversion

Template: Dave **Create Template**

Types: ALL

Pulse Code: Search

Notes:
 The Pulse-to-Contact ID conversion template maps Pulse event codes to their corresponding Contact ID event codes, enabling consistent and accurate translation of security events. Technicians must download and apply the updated template to all associated radio modules to ensure customized event reporting to the central station. Failure to apply the modified template will result in the use of default or previously configured event codes.

| Pulse Code | Type | Code Name | Default CID Event Code | CID Event Code |
|------------|-------|---------------|------------------------|----------------|
| 11 | Alarm | Keypad Fire | 179AA981 | 113AA1AA |
| 12 | Alarm | Not Define 12 | 179AA981 | 179AA981 |
| 13 | Alarm | Not Define 13 | 179AA981 | 179AA981 |

4. **To edit a code:** Referring to the screen in step 3, select the code in the **CID Event Code** column. The **EDIT FORM** dialog opens:

EDIT FORM

Pulse Code: 11

Default CID Event Code: 179AAA9815

Event Type: Alarm

CID Event Code: 790

Area No: 00

Zone No: 981

Code Name: Not Define 11

Save Close

To configure a template or create a new one: Select a template from the **Template** drop-down and select **Create Template** (changes to the Default Template are not permitted).

Template: Dave **Create Template**

Types: ALL

Pulse Code: Search

The **Template Configuration** screen opens (shown below). Select a template from the **Template Selection** list, then type a **New Template Name**.

Select **Save Template** to retain or select **Delete Template** to discard your changes.

Template Configuration

Template Selection: >> Assigned Radio

Default Template
 test 1
 jack testing
 Howie
 Joe 1
 Joe2 8831

New Template Name:

Save Template Delete Template Close

IMPORTANT: Always perform an upload and verify the template after saving a template to the communicator.

ALWAYS VERIFY EVERY PULSE 4/2 TO CONTACT ID CONVERSION BEFORE LEAVING THE PREMISES.

NAPCO LIMITED WARRANTY

NAPCO SECURITY TECHNOLOGIES, INC. (NAPCO) warrants its products to be free from manufacturing defects in materials and workmanship for *thirty-six months* following the date of manufacture. NAPCO will, within said period, at its option, repair or replace any product failing to operate correctly without charge to the original purchaser or user.

This warranty shall not apply to any equipment, or any part thereof, which has been repaired by others, improperly installed, improperly used, abused, altered, damaged, subjected to acts of God, or on which any serial numbers have been altered, defaced or removed. Seller will not be responsible for any dismantling or reinstallation charges.

THERE ARE NO WARRANTIES, EXPRESS OR IMPLIED, WHICH EXTEND BEYOND THE DESCRIPTION ON THE FACE HEREOF. THERE IS NO EXPRESS OR IMPLIED WARRANTY OF MERCHANTABILITY OR A WARRANTY OF FITNESS FOR A PARTICULAR PURPOSE. ADDITIONALLY, THIS WARRANTY IS IN LIEU OF ALL OTHER OBLIGATIONS OR LIABILITIES ON THE PART OF NAPCO.

Any action for breach of warranty, including but not limited to any implied warranty of merchantability, must be brought within the six months following the end of the warranty period. IN NO CASE SHALL NAPCO BE LIABLE TO ANYONE FOR ANY CONSEQUENTIAL OR INCIDENTAL DAMAGES FOR BREACH OF THIS OR ANY OTHER WARRANTY, EXPRESS OR IMPLIED, EVEN IF THE LOSS OR DAMAGE IS CAUSED BY THE SELLER'S OWN NEGLIGENCE OR FAULT.

In case of defect, contact the security professional who installed and maintains your security system. In order to exercise the warranty, the product must be returned by the security professional, shipping costs prepaid and insured to NAPCO. After repair or replacement, NAPCO assumes the cost of returning products under warranty. NAPCO shall have no obligation under this warranty, or otherwise, if the product has been repaired by others, improperly installed, improperly used, abused, altered, damaged, subjected to accident, nuisance, flood, fire or acts of God, or on which any serial numbers have been altered, defaced or removed. NAPCO will not be responsible for any dismantling, reassembly or reinstallation charges.

This warranty contains the entire warranty. It is the sole warranty and any prior agreements or representations, whether oral or written, are either merged herein or are expressly cancelled. NAPCO neither assumes, nor authorizes any other person purporting to act on its behalf to modify, to change,

or to assume for it, any other warranty or liability concerning its products.

In no event shall NAPCO be liable for an amount in excess of NAPCO's original selling price of the product, for any loss or damage, whether direct, indirect, incidental, consequential, or otherwise arising out of any failure of the product. Seller's warranty, as hereinabove set forth, shall not be enlarged, diminished or affected by and no obligation or liability shall arise or grow out of Seller's rendering of technical advice or service in connection with Buyer's order of the goods furnished hereunder.

NAPCO RECOMMENDS THAT THE ENTIRE SYSTEM BE COMPLETELY TESTED WEEKLY.

Warning: Despite frequent testing, and due to, but not limited to, any or all of the following; criminal tampering, electrical or communications disruption, it is possible for the system to fail to perform as expected. NAPCO does not represent that the product/system may not be compromised or circumvented; or that the product or system will prevent any personal injury or property loss by burglary, robbery, fire or otherwise; nor that the product or system will in all cases provide adequate warning or protection. A properly installed and maintained alarm may only reduce risk of burglary, robbery, fire or otherwise but it is not insurance or a guarantee that these events will not occur. CONSEQUENTLY, SELLER SHALL HAVE NO LIABILITY FOR ANY PERSONAL INJURY, PROPERTY DAMAGE, OR OTHER LOSS BASED ON A CLAIM THE PRODUCT FAILED TO GIVE WARNING. Therefore, the installer should in turn advise the consumer to take any and all precautions for his or her safety including, but not limited to, fleeing the premises and calling police or fire department, in order to mitigate the possibilities of harm and/or damage.

NAPCO is not an insurer of either the property or safety of the user's family or employees, and limits its liability for any loss or damage including incidental or consequential damages to NAPCO's original selling price of the product regardless of the cause of such loss or damage.

Some states do not allow limitations on how long an implied warranty lasts or do not allow the exclusion or limitation of incidental or consequential damages, or differentiate in their treatment of limitations of liability for ordinary or gross negligence, so the above limitations or exclusions may not apply to you. This Warranty gives you specific legal rights and you may also have other rights which vary from state to state.